

# Power SE

Smart Wi-Fi power plug

15A | on/off manual & automatic



smart me



- Plug & play
- No hub
- One app
- Voice control
- Create scenarios



## EN

- Plug & play; no gateway or software required.
- Use the **Smart me** app to set timings for switching on/off automatically.
- Use the **Smart me** app to allow different Marmitek smart products to communicate with each other.
- Possible to turn on/off manually.

## NL

- Plug & play; geen gateway of software benodigd.
- Gebruik de **Smart me** app om timings in te stellen voor het automatisch aan- of uitzetten.
- Gebruik de **Smart me** app om nog meer Marmitek smart producten met elkaar te laten communiceren.
- Mogelijk om handmatig aan/uit te zetten.

## DE

- Plug & Play; kein Gateway oder Software erforderlich.
- Verwenden Sie die **Smart me** App, um die Zeiten für das automatische Ein- und Ausschalten festzulegen.
- Mit der **Smart me** App können noch mehr Marmitek-Smart-Produkte miteinander kommunizieren.
- Manuelles Ein- und Ausschalten möglich.

## FR

- Plug & play ; pas besoin de passerelle ou de logiciel.
- Utilisez l'application **Smart me** pour définir les horaires d'activation ou de désactivation automatique.
- Utilisez l'application **Smart me** afin de permettre à encore plus de produits intelligents Marmitek de communiquer entre eux.
- Possibilité d'allumer/éteindre manuellement.

## ES

- Plug & play; sin gateway o software.
- Ajustar temporizador para encender/apagar automáticamente con la **Smart me** app.
- Activar la comunicación entre aun mas productos inteligentes de Marmitek con la **Smart me** app.
- Opción de encender/apagar manualmente.

## IT

- Plug & play; nessun gateway o software richiesto.
- Utilizza l'app **Smart me** per impostare i tempi di accensione/spengimento automaticamente.
- Usa l'app **Smart me** per consentire ad altri prodotti intelligenti Marmitek di comunicare tra loro.
- Possibilità di accendere/spengere manualmente.

stay connected

**MARMITEK**®

# Power SE



energy &  
power saving



plug & play



control  
from anywhere



expandable

<b>Power outlet</b>	1x 100–240 V socket
<b>Max. output and current</b>	3450 W – 15 A   IEC type E,F 3000 W – 13 A   IEC type G
<b>Wireless technology</b>	Wi-Fi 2.4 GHz
<b>Power</b>	100–240 VAC 50/60 Hz
<b>Standby current</b>	< 0.5 W
<b>Dimensions (h x w x d)</b>	72 x 52 x 72 mm



**Set includes:** 1x power plug + quick guide

## Control your electrical devices from anywhere with the Marmitek



smart me app



smart me sensors



or your voice

Download the **Smart me app** on:



**Compatible with:**

Amazon Alexa | Google Assistant | Apple Siri

## Order information

### Power SE

Art. no. 08516 – IEC type F EAN 8718164535161  
Art. no. 08517 – IEC type G EAN 8718164535178  
Art. no. 08518 – IEC type E EAN 8718164535185  
Art. no. 08540 – IEC type J EAN 8718164535406

Packaging size (h x w x d): 130 x 80 x 80 mm

In order to continue improving the product, Marmitek reserves the right to change specifications and/or designs without prior notice.

[www.marmitek.com](http://www.marmitek.com)

22946/20200706