



SAVA 1026 Smart AV HDMI auto switcher

Key Benefits

- This UltraHD HDMI Switch allows you to connect up to 4 peripheral devices to your TV with just one cable
- Connect 4 HDMI devices with 1 HDMI cable
- Suitable for the latest Ultra HD 4K60 resolution
- Supports HDCP 2.2 for 4K Ultra HD content

**Combines 4 HDMI connections into 1 connection.
Switches automatically between the connected devices.
HDMI hub for 4 devices**

The SAVA 1026 allows you to connect 4 HDMI devices to your TV. Suitable for the latest Ultra HD 4K resolution. Supports Dolby Atmos and DTS:X, as well as other popular audio formats. The built-in repeater and equaliser prevent signal loss. HDCP 2.2 support provides secure 4K Ultra HD content.





SAVA 1026 Smart AV HDMI auto switcher

Specifications

Article number (SKU)	8310263
Colour	Anthracite metal
EAN single box	8712285339608
Guarantee	2 years
Audio formats	Dolby Digital/AC3 Dolby TrueHD DTS 5.1 DTS:X DTS-HD Master Audio Dolby Atmos PCM stereo
AV input	4x HDMI
AV output	1x HDMI 1x HDMI 1x HDMI 1x HDMI 1x HDMI 1x HDMI 1x HDMI 1x HDMI 1x HDMI
Certifications	CE
Clock frequency	600
Colour formats	YCbCr 4:2:0 YCbCr 4:4:4 RGB YCbCr 4:2:2
HDCP standard	HDCP 1.4/2.2
HDMI standard	CEC Deep Color 36-bit DVI EDID HDMI 2.0b HDR
HDTV resolution	Max. 2160@60Hz
Power supply	100-240 VAC 50/60 Hz, 5 VDC adapter 100-240 VAC 50/60 Hz, 5 VDC adapter 100-240 VAC 50/60 Hz, 5 VDC-Adapter 100-240 VAC 50/60 Hz, 5 adattatori VDC 100-240 VAC 50/60 Hz, Adaptateur 5 VDC 100-240 VAC 50/60 Hz, Adaptador de 5 VCC 100-240 VAC 50/60 Hz, Адаптер питания 5 В постоянного тока 100-240 VAC 50/60 Hz, Zasilacz 5 V DC 100-240 VAC 50/60 Hz, 5 VDC-adapter
Video bandwidth	18

VOGEL'S HOLDING BV (©)

All rights reserved.
Subject to printing errors,
technical and price
amendments.

Date: 2023-01-14